

Model Number

NRB15-30GM50-E2-IO-C-V1

Features

- 15 mm flush ٠
- Reduction factor = 1 .
- Magnetic field resistant
- Weld Immune
- IO-link interface for service and process data
- Switch point mode or window mode can be set
- Switching function, stability alarm and pulse extension can be set

Description

Reduction factor 1 sensors reliably detect different metals with the same switch state. The integrated IO-Link interface enables clear identification of the sensor and diagnosis of the sensor condition. When using the sensor, parameters and operating modes can be optimally configured specifically for the intended application. In addition to setting the switching function and a pulse extension, the user can select either switch point mode or window mode in combination with a stability alarm. In switch point mode, the stability alarm signals the detection of an object in the area between the assured operating distance and operating distance $\boldsymbol{s}_n.$ In window mode, it signals the detection of an object below the window between operating distance \boldsymbol{s}_n and the nearest operating distance. A stability alarm is displayed to the user via a flashing LED and process data.

Accessories

IO-Link-Master02-USB IO-Link master, supply via USB port or separate power supply, LED indicators, M12 plug for sensor connection BF 30 Mounting flange, 30 mm EXG-30 Quick mounting bracket with dead stop V1-G Female connector, M12, 4-pin, field attachable V1-W Female connector, M12, 4-pin, field attachable V1-G-2M-PUR Female cordset, M12, 4-pin, PUR cable V1-W-2M-PUR Female cordset, M12, 4-pin, PUR cable

Technical Data	
General specifications	
Switching function	
Output type	
Rated operating distance	s _n
Near operating distance	
Installation	
Output polarity	
Assured operating distance	s _a
Reduction factor r _{Al}	
Reduction factor r _{Cu} Reduction factor r ₃₀₄	
Reduction factor r _{St37}	
Output type	
Nominal ratings	
Operating voltage	UB
Switching frequency	f
5 - 1	
Hysteresis	Н
Reverse polarity protection	
Short-circuit protection	
Voltage drop	Ud
Operating current	IL.
Off-state current	l _r
No-load supply current	l _o
Time delay before availability Constant magnetic field	t _v B
Alternating magnetic field	В
Status indicator	U
Functional safety related parameter	ers
MTTF _d	
Mission Time (T _M)	
Diagnostic Coverage (DC)	
Interface	
Interface type	
Transfer rate	
IO-Link Revision	
Min. cycle time	
Process data witdh	
SIO mode support	
Device ID	
Compatible master port type	
Ambient conditions	
Ambient temperature	
Storage temperature	
Mechanical specifications	
Connection type Housing material	
Sensing face	
Degree of protection	
Mass	
Factory settings	
Default setting	
General information	
Scope of delivery	
Compliance with standards and	
directives	
Standard conformity	
Standards	
Approvale and equificates	
Approvals and certificates	
Protection class	
Rated insulation voltage	Ui
Rated impulse withstand voltage	Uim

NRB15-30GM50-E2-IO-C-V1

Normally open/closed (NO/NC) programmable
PNP
15 mm (factory setting)
10 mm (can be activated by software)
flush
DC
0 12.15 mm
1
1
1
1
3-wire
10 30 V DC
0 600 Hz (switch point mode)
0 25 Hz (window mode, switch point mode with stability alarm)
typ. 3 %
reverse polarity protected
pulsing
≤ 0.5 V
0 200 mA
0 0.5 mA typ. 60 μA at 25 °C
≤ 15 mA
≤ 150 ms
200 mT
200 mT
Multihole-LED, yellow
362 a
20 a
0 %
IO-Link (via C/Q = pin 4)
COM 2 (38.4 kBaud)
1.1
2.3 ms
Process data input (control system side): 2 Bit
Process data output (control system side): none
yes
0x201113 (2101523)
A
-25 70 °C (-13 158 °F)
-40 85 °C (-40 185 °F)
Connector plug M12 x 1 4-pip
Connector plug M12 x 1 , 4-pin Brass, PTFE coated
,
PPS
IP67
156 g
operating mode = switch point mode with stability alarm
operating mode = switch point mode with stability alarm switching function = Normally open (NO)
switching function = Normally open (NO)
switching function = Normally open (NO) switching distance = 15 mm
switching function = Normally open (NO)
switching function = Normally open (NO) switching distance = 15 mm
switching function = Normally open (NO) switching distance = 15 mm
switching function = Normally open (NO) switching distance = 15 mm
switching function = Normally open (NO) switching distance = 15 mm 2 self locking nuts in scope of delivery EN 60947-5-2:2007
switching function = Normally open (NO) switching distance = 15 mm 2 self locking nuts in scope of delivery
switching function = Normally open (NO) switching distance = 15 mm 2 self locking nuts in scope of delivery EN 60947-5-2:2007 EN 60947-5-2/A1:2012
switching function = Normally open (NO) switching distance = 15 mm 2 self locking nuts in scope of delivery EN 60947-5-2:2007 EN 60947-5-2:/A1:2012 IEC 60947-5-2:2007
switching function = Normally open (NO) switching distance = 15 mm 2 self locking nuts in scope of delivery EN 60947-5-2:2007 EN 60947-5-2/A1:2012
switching function = Normally open (NO) switching distance = 15 mm 2 self locking nuts in scope of delivery EN 60947-5-2:2007 EN 60947-5-2/A1:2012 IEC 60947-5-2:2007 IEC 60947-5-2 AMD 1:2012
switching function = Normally open (NO) switching distance = 15 mm 2 self locking nuts in scope of delivery EN 60947-5-2:2007 EN 60947-5-2/A1:2012 IEC 60947-5-2:2007 IEC 60947-5-2 AMD 1:2012
switching function = Normally open (NO) switching distance = 15 mm 2 self locking nuts in scope of delivery EN 60947-5-2:2007 EN 60947-5-2:A11:2012 IEC 60947-5-2:2007 IEC 60947-5-2:AMD 1:2012 IEC 60947-5-2 AMD 1:2012
switching function = Normally open (NO) switching distance = 15 mm 2 self locking nuts in scope of delivery EN 60947-5-2:2007 EN 60947-5-2/A1:2012 IEC 60947-5-2:2007 IEC 60947-5-2 AMD 1:2012
switching function = Normally open (NO) switching distance = 15 mm 2 self locking nuts in scope of delivery EN 60947-5-2:2007 EN 60947-5-2:2007 IEC 60947-5-2:2007 IEC 60947-5-2 AMD 1:2012 II 60 V 800 V
switching function = Normally open (NO) switching distance = 15 mm 2 self locking nuts in scope of delivery EN 60947-5-2:2007 EN 60947-5-2:/A1:2012 IEC 60947-5-2:2007 IEC 60947-5-2:AMD 1:2012 II 60 V 800 V cULus Listed, General Purpose
switching function = Normally open (NO) switching distance = 15 mm 2 self locking nuts in scope of delivery EN 60947-5-2:2007 EN 60947-5-2:2012 IEC 60947-5-2:2007 IEC 60947-5-2 AMD 1:2012 II 60 V 800 V

eng.xml

Refer to "General Notes Relating to Pepperl+Fuchs Product Information"

Pepperl+Fuchs Group www.pepperl-fuchs.com

USA: +1 330 486 0001 fa-info@us.pepperl-fuchs.com

Germany: +49 621 776 1111 fa-info@de.pepperl-fuchs.com


UL approval

CCC approval


Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com

⁵ PEPPERL+FUCHS

Dimensions



Electrical Connection



Pinout



Wire colors in accordance with EN 60947-5-2

1	BN	(brown)
2	WH	(white)
3	BU	(blue)
4	BK	(black)

Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com

FEPPERL+FUCHS

Switching output modes


Switch point mode at rated operating distance sn

Switch point 2 SP 2 (rated operating distance sn)




Switch point mode with near operating distance

Switch point 1 SP1 (near operating distance)



Window mode


Switch point 2 SP 2 (rated operating distance $s_{n)}$



Stability alarm


Switch point mode with stability alarm (factory default)

Switch point 2 SP 2 (rated operating distance sn)



Window mode with stability alarm

Switch point 2 SP 2 (rated operating distance sn)



Release date: 2019-06-05 09:47 Date of issue: 2019-06-05 306533-0009_eng.xml

Refer to "General Notes Relating to Pepperl+Fuchs Product Information"

Pepperl+Fuchs Group www.pepperl-fuchs.com USA: +1 330 486 0001 fa-info@us.pepperl-fuchs.com Germany: +49 621 776 1111 fa-info@de.pepperl-fuchs.com Singapore: +65 6779 9091 fa-info@sg.pepperl-fuchs.com