









### **Model Number**

NRB4-12GS40-E2-IO-V1

## **Features**

- 4 mm flush
- Reduction factor = 1
- Magnetic field resistant
- IO-link interface for service and process data
- Switch point mode or window mode can be set
- Switching function, stability alarm and pulse extension can be set

## Description

Reduction factor 1 sensors reliably detect different metals with the same switch state. The integrated IO-Link interface enables clear identification of the sensor and diagnosis of the sensor condition. When using the sensor, parameters and operating modes can be optimally configured specifically for the intended application. In addition to setting the switching function and a pulse extension, the user can select either switch point mode or window mode in combination with a stability alarm. In switch point mode, the stability alarm signals the detection of an object in the area between the assured operating distance and operating distance s<sub>n</sub>. In window mode, it signals the detection of an object below the window between operating distance  $s_n$ and the nearest operating distance. A stability alarm is displayed to the user via a flashing LED and process data.

## **Accessories**

## IO-Link-Master02-USB

IO-Link master, supply via USB port or separate power supply LED indicators, M12 plug for sensor connection

BF 12 Mounting flange, 12 mm

306533-0013

2019-06-05

issue:

Date of

Release date: 2019-06-05 09:46

EXG-12

Quick mounting bracket with dead stop

V1-G

Female connector, M12, 4-pin, field attachable

V1-W Female connector, M12, 4-pin, field attachable

V1-G-2M-PVC

Female cordset, M12, 4-pin, PVC cable

V1-W-2M-PVC

Female cordset, M12, 4-pin, PVC cable

## **Technical Data**

#### **General specifications**

Switching function Normally open/closed (NO/NC) programmable Output type
Rated operating distance PNP 4 mm (factory setting) Near operating distance 3 mm (can be activated by software) Installation flush Output polarity Assured operating distance DC 0 ... 3.24 mm Reduction factor rAI Reduction factor r<sub>Cu</sub> Reduction factor r<sub>304</sub> Reduction factor r<sub>St37</sub> Output type

## Nominal ratings

Operating voltage  $\mathsf{U}_\mathsf{B}$ 10 ... 30 V DC Switching frequency 0 ... 2000 Hz (switch point mode)

0 ... 125 Hz (window mode, switch point mode with stability alarm) Н Hysteresis tvp. 3 %

Reverse polarity protection reverse polarity protected Short-circuit protection pulsing Voltage drop  $U_d$ ≤ 0.5 V 0 ... 200 mA

Operating current Off-state current 0 ... 0.5 mA typ. 60  $\mu A$  at 25 °C No-load supply current Time delay before availability ≤ 150 ms t<sub>v</sub> B 200 mT Constant magnetic field

Alternating magnetic field В 200 mT Status indicator Multihole-LED, yellow

Functional safety related parameters 362 a Mission Time (T<sub>M</sub>) 20 a Diagnostic Coverage (DC)

Interface

Interface type IO-Link ( via C/Q = pin 4 ) COM 2 (38.4 kBaud) Transfer rate

IO-Link Revision 1.1 Min. cycle time 2.3 ms

Process data witdh Process data input (control system side): 2 Bit Process data output (control system side): none

SIO mode support 0x201101 (2101505)

Compatible master port type Ambient conditions

-25 ... 70 °C (-13 ... 158 °F) -40 ... 85 °C (-40 ... 185 °F) Ambient temperature Storage temperature

Mechanical specifications

Connector plug M12 x 1 , 4-pin Stainless steel 1.4305 / AISI 303 Connection type

Housing material Sensing face PBT Degree of protection **IP67** Mass 25 g

**Factory settings** 

Default setting operating mode = switch point mode with stability alarm

switching function = Normally open (NO) switching distance = 4 mm

IEC 60947-5-2 AMD 1:2012

General information

Scope of delivery 2 self locking nuts in scope of delivery

Compliance with standards and

directives

Standard conformity Standards

EN 60947-5-2:2007 EN 60947-5-2/A1:2012 IEC 60947-5-2:2007

Approvals and certificates


Protection class 60 V Rated insulation voltage 800 V Rated impulse withstand voltage

cULus Listed, General Purpose **UL** approval


Class 2 power source

CCC approval CCC approval / marking not required for products rated ≤36 V

# **Dimensions**



# **Electrical Connection**



# **Pinout**



Wire colors in accordance with EN 60947-5-2


1	BN	(brown)
2	WH	(white)
3	BU	(blue)
1	DK.	(black)

**FPPPERL+FUCHS** 


#### Switching output modes

## Switch point mode at rated operating distance $\boldsymbol{s}_n$


Switch point 2 SP 2 (rated operating distance s<sub>n)</sub>



#### Switch point mode with near operating distance




#### Window mode



### Stability alarm

Switch point mode with stability alarm (factory default)



Window mode with stability alarm

Switch point 2 SP 2 (rated operating distance  $s_n$ )

