



## KDRAA6H2

KDR, 480V, 4 HP, 6.20 Motor Amps, 7.6 Max Amps, Narrow Foot, 3 Phase, Open, Line Inductor, 5% Impedance. UL Listed.

## PRODUCT INFORMATION

SKU: KDRAA6H2. Categories: Input, Line Reactor, KDR.

## SPECIFICATIONS

|                        |   |
|------------------------|---|
| <b>Rated Voltage</b>   | 480   |
| <b>Hertz (Hz)</b>      | 50/60   |
| <b>Horsepower (HP)</b> | 4   |
| <b>kVAR</b>            | 0   |
| <b>Phase</b>           | 3   |
| <b>Max Amps</b>        | 7.6   |
| <b>UL</b>              | UL Listed   |
| <b>Enclosure Type</b>  | Open  |
| <b>Watts Loss</b>      | 50.2  |
| <b>RoHS Indicator</b>  | Compliant   |
| <b>Dimensions</b>      | Height: 4.44 in<br>Width: 4.25 in<br>Depth: 2.64 in |
| <b>Weight</b>          | 3.4 lbs   |

Contact TCI for more information or to place an order:  
800-824-8282 | sales@transcoil.com | transcoil.com  
W132 N10611 Grant Drive, Germantown, WI 53022