



## PRODUCT INFORMATION

SKU: KDRJ43L. Categories: Input, Line Reactor, KDR.

## SPECIFICATIONS

|                          |                                             |
|--------------------------|---------------------------------------------|
| <b>Rated Voltage</b>     | 575                                         |
| <b>Hertz (Hz)</b>        | 50/60                                       |
| <b>Horsepower (HP)</b>   | 400                                         |
| <b>Phase</b>             | 3                                           |
| <b>Amps</b>              | 385                                         |
| <b>Impedance Value</b>   | Low Z                                       |
| <b>UL</b>                | UL Listed                                   |
| <b>Enclosure Type</b>    | Open                                        |
| <b>Watts Loss</b>        | 463                                         |
| <b>Country of Origin</b> | US                                          |
| <b>RoHS Indicator</b>    | Compliant                                   |
| <b>Dimensions</b>        | Height: 9 in<br>Width: 11 in<br>Depth: 9 in |
| <b>Weight</b>            | 70 lbs                                      |



## KDRJ43L

KDR, 575V, 385A, 400HP, 3 Phase, Open, Input Line Inductor, Low Impedance, UL Listed

Contact TCI for more information or to place an order:  
800-824-8282 | sales@transcoil.com | transcoil.com

W132 N10611 Grant Drive, Germantown, WI 53022